






單相、三相固態繼電器

SSR

認證：CE

外觀	DC→AC 	DC→DC 	DC→DC 	AC→AC 
產品名稱	單相固態繼電器 (SSR)			
型號	SSR-10DA-(H) SSR-50DA-(H) SSR-15DA-(H) SSR-75DA-(H) SSR-25DA-(H) SSR-90DA-(H) SSR-40DA-(H) SSR-100DA-(H)	SSR-20D SSR-40D	SSR-5DD SSR-40DD-(H) SSR-10DD-(H) SSR-50DD-(H) SSR-25DD-(H) SSR-75DD-(H)	SSR-10AA-(H) SSR-50AA-(H) SSR-15AA-(H) SSR-75AA-(H) SSR-25AA-(H) SSR-90AA-(H) SSR-40AA-(H) SSR-100AA-(H)
控制電壓範圍	4-32 VDC	3-32 VDC	3-32 VDC	80-280 VAC
最大截止電壓	1 VDC	1 VDC	1 VDC	10 VAC
最大負載電流 (25°C)	10A 50A 15A 75A 25A 90A 40A 100A	2A 4A	5A 40A-(H) 10A-(H) 50A-(H) 25A-(H) 75A-(H)	10A 50A 15A 75A 25A 90A 40A 100A
負載電壓範圍	24-280VAC 48-480VAC (H)	3-60 VDC	5-120VDC 5-240VDC (H)	24-280VAC 48-480VAC (H)
破壞電壓	600V 1200V (H) PEAK	80VDC	140VDC 300VDC (H)	600V 1200V (H) PEAK
控制方式	零點觸發	N/A	N/A	零點觸發

外觀	VR→AC 							
產品名稱	可變電壓器繼電器 (SSVR)	三相固態繼電器(3 Phase SSR)		I/O模組(I/O Module) 1/2/4/8 port				
型號	SSR-10RA SSR-15RA SSR-25RA-(H) SSR-40RA-(H)	SSR-3PH_DA-(H)	SSR-3PH_AA-(H)	SSR-3PH_DA-(H)	SSR-3PH_AA-(H)	IO-X-20	IO-X-0604D	
		DC → AC	AC → AC	DC → AC	AC → AC	DC → AC	DC → DC	
控制電壓範圍	VR500KΩ	VR1MΩ	6-32 VDC 12-32 VDC(H)	80-280VCA	6-32 VDC 12-32 VDC(H)	80-280VCA	3-32 VDC	
最大截止電壓			3 VDC 9.5 VDC(H)	10 VDC	3 VDC 9.5 VDC(H)	10 VDC	1 VDC	
最大負載電流 (25°C)	10A 15A 25A(H) 40A(H)		25A 50A 40A 75A 90A 100A		25A 50A 40A 75A 90A 100A		2A 4A	
負載電壓範圍	24-280VAC 48-480VAC (H)		24-280VAC 48-480VAC (H)		24-280VAC 48-480VAC (H)		24-280VAC 48-480VAC (H)	3-32VDC
破壞電壓	600V 1200V (H) PEAK		600V 1200V (H) PEAK	600V 1200V (H) PEAK	600V 1200V (H) PEAK	600V 1200V (H) PEAK	600V 1200V (H) PEAK	60VDC
控制方式	相位控制		零點觸發	零點觸發	隨機觸發	隨機觸發	零點觸發	N/A

H